

## Additional LKV379P-DVB-T Instructions

Some Samsung TV's need their own Network ID, change it to 65535 (Option 1.3)

Some LG TV's need their own ONID, change it from AUTO (Option 1.4)

If you are using multiple modulators then the following options need to have their own, unique identifier numbers.

### **1. STREAM**

1.1 TSID – 1 (*default setting*)

1.2 ONID - AUTO <- *Needs to be changed for multiple LKV379P-DVB-T*

1.3 NETWORK ID – AUTO <- *Needs to be changed for multiple LKV379P-DVB-T*

1.3 SERVICE NAME - TV <- *Needs to be changed for multiple LKV379P-DVB-T*

1.4 SERVICE ID - 1 <- *Needs to be changed for multiple LKV379P-DVB-T*

1.6 LCN MODE - European

1.7 LCN ID - 800 <- *Needs to be changed for multiple LKV379P-DVB-T*

### **2. MODULATOR**

2.1 COUNTRY - New Zealand

2.2 CHANNEL - Chan 25 506.0MHz <- *Needs to be changed for multiple LKV379P-DVB-T*

2.3 VIDEO BITRATE - 18

2.4 AUDIO BITRATE - 192

2.5 AUDIO FORMAT - MPEG

2.6 AUDIO SYNC – 700 <- *Lip sync adjustment*

### **3. ADVANCED**

3.1 BANDWIDTH - 8M

3.2 CONSTELLATION - 64QAM

3.3 FEC - 7/8

3.4 GUARD INTERVAL - 1/32

3.5 CARRIER RATE - 8K

3.6 DB LEVEL - 0dBm

### **4. SYSTEM**

4.1 VERSION

4.2 RESET