

600W DC TO AC POWER INVERTER

DESCRIPTION

DYNAMIX Modified sine wave power inverters include 2x USB ports and standard AC power outlet(s). The DYNAMIX inverters are perfect for charging mobile phones, tablets, notebooks plus many other devices that need power on the go. The DYNAMIX inverters are solid, durable, and built to last. The 2x USB charging ports will detect your devices power requirements and deliver best matched charging current to ensure your device is protected from over-charging or over-loading.

FEATURES

- 600W Modified Sine wave power inverter
- ON/OFF switch. Turns the inverter ON and OFF
- 2x Standard AC outlet
- 2x USB ports (5V, 2.1A + 1.0A)
- High speed cooling fan
- Overheat and overload protected
- Low voltage alarm
- Positive power input terminal
- Negative power input terminal
- Alligator clips included



PRODUCT CODE

TE6-1635P0600

DESCRIPTION

600W Power Inverter

COLOUR

Black/Grey

SPECIFICATIONS

Continues Power	600W
Surge Capacity	1200W
AC Output Voltage Range	230V AC
AC Output Frequency	50Hz
Output Waveform	Modified Sine Wave (MSW)
USB Output Ports	2x Ports (3100mAh Shared)
AC Output Socket	2x Standard Port
Battery Low Alarm	10.5V
Low Battery Shut-down	10.5V
Internal Fuse	2x 35A Fuses
Positive Power Input Terminal	Yes
Negative Power Input Terminal	Yes
High Speed Cooling Fan	Yes
12V Connector	No
Dimensions (LxWxH)	195x155x75mm

Please note we took the up-most care to compile the information in this datasheet. To the best of our knowledge all info provided were correct at the time of creation. Should any specs change we try to update info accordingly. Information are subject to change without notice. In the case that you find any irregularity please inform our team at contactus@dynamix.co.nz

Last updated: 8 October 2019